

Dimmer Compatibility Guide

776872 LED5A19/27K/FIL/3

				Lamps per Dimmer			
	Manufacturer	Product	Model Number	Overall Rating	Recommended Minimum	Maximum Tested*	Notes
Incandescent/Halogen (Triac/Phase Cut/Leading Edge Dimmers)	Leviton	IllumaTech	IPI06	Best	1	6	Dims down to 13%
		SureSlide	6633-P	Best	1	6	Dims down to 1%
		Vizia	VPI06-1LZ	Best	2	6	Dims down to 8%
	Lutron	Toggler	TG-600	Best	1	6	Dims down to 7%
		Diva	DV-600	Best	1	6	Dims down to 1%
		Skylark	S-600	Best	1	6	Dims down to 1%
		Maestro	MAW-600	Good	2	6	Dims down to 1%
	Legrand	Titan	CD703-PW	Best	1	6	Dims down to 15%
		Harmony	D703-PTC	Best	1	6	Dims down to 1%
		Harmony	H703-PTC	Best	1	6	Dims down to 1%
CFL/LED	Leviton	IllumaTech	IPL06	Best	1	6	Dims down to 1%
		Sureslide	6674	Best	1	6	Dims down to 11%
		Decora	6672	Best	1	6	Dims down to 6%
		Decora Slide	DSL06-1LZ	Best	1	6	Dims down to 11%
	Lutron	Skylark	CTCL-153	Best	1	6	Dims down to 1%
		Diva	DVCL-153PL	Best	1	6	Dims down to 1%
		Maestro	MACL-153MLH	Best	1	6	Dims down to 6%
		Skylark	SCL-153P	Best	1	6	Dims down to 1%
		Toggler	TGCL-153PH	Best	1	6	Dims down to 1%
		Radio RA	RA2RR-6CL-PD	Best	1	6	Dims down to 4%
	Legrand	Harmony	DCL453-PTC	Best	1	6	Dims down to 4%
		Harmony	HCL453PTC	Best	1	6	Dims down to 10%
		Adorne Paddle	ADPD453LM2	Bad	1	6	Dims down to 35%
		raome radae	7101 0433EHE	500	-		5 m 5 down to 55%
	Leviton	Vizia	VPE04	Best	1	6	Dims down to 14%
		IllumaTech	IPE04	Best	1	6	Dims down to 10%
		Decora	6615-P	Bad	1	6	Dims down to 50%
Electronic Low Voltage	Lutron	Skylark Countour	CTELV-303P	Best	1	6	Dims down to 12%
		Diva	DVELV-300P	Best	1	6	Dims down to 12%
		Maestro	MAELV-600	Best	1	6	Dims down to 12%
		Skylark	SELVB-300P	Best	1	6	Dims down to 12%
		VIERTI	VTEL-600M-W	Best	1	6	Dims down to 12%
-	Legrand	Scene Director	SCELV	Good	1	6	Dims down to 31%
	Legianu	Scene Birector	SCEEV	dood	1	Ü	Dillis down to 31%
Magentic Low Voltage	Leviton	Vizia	VPM-06	Good	2	6	Dims down to 8%
		Decora	6613-P	Best	1	6	Dims down to 2%
	Lutron	Maestro	MALV-600	Good	2	6	Dims down to 7%
	Lution	Harmony	DLV703-PW	Best	1	6	Dims down to 1%
	Legrand	Titan	CDLV703-PW	Best	1	6	Dims down to 1% Dims down to 15%
	Legianu	Ittali	CD24703-1 44	Dest	1	· ·	Dinis down to 15%
	Leviton	Decora Digital (Bluetooth)	DDMX1-BLZ	Best	1	6	Dims down to 10%
Smart Dimmer	Leviton	Decora Smart Z-Wave Technology	DZ6HD	Best	1	6	Dims down to 10%
	Lutron	Caseta Wireless smart dimmer Wi-Fi	PD-10NXD	Best	1	6	Dims down to 7%
	Lutron	Caseta Wireless smart dimmer Wi-Fi	PD-10NXD PD-6WCL	Best	1	6	Dims down to 12%
	Lutron	Adorne touch Wi-Fi TRU Universal	ADTH700RMTUW1	pest	1	0	DITTS GOWIT tO 1276
	Legrand	Adorne Sof Tap Wi-Fi TRU Universal	ADTP700RMTUW1				
	GE	Z WAVE	ZW3005	Best	1	6	Dims down to 1%
	GE	ZVVMVE	ZVV 30U3	pest	1	0	Dinis down to 1%
Universal	Legrand	Adorne SofTap	ADTP703TU	Best	1	6	Dims down to 11%
		Miro Decorator	DRD4-W	Best	1	6	Dims down to 11% Dims down to 3%
				Bad	_	6	
		Harmony	H703PTUTC		1		Dims down to 40%
Olliversal		Adorne Whisper	ADWR700MMTUW2	Best	1	6	Dims down to 1%
	Cooper	Adorne Touch	ADTH700MMTUM2	Best	1	6	Dims down to 1%
		Decorator	DAL06P-C2-K-L	Best	1	6	Dims down to 1%
		Skye	SAL06P-W-K-L	Best	1	6	Dims down to 1%

*Maximum Tested (Lamps per Dimmer) - Additional lamps may work with your dimmer system. For maximum capacity please consult dimmer manufacturer.

*May experience "pop-on", lights cannot be turned on immediately to their minimum level. The slider needs to be raised above the minimum light level for the lights to first turn on if they were initially off. Then, the slider can be lowered to get to a lower light level; the dimmer cannot be turned on to just the minimum level.

Overall Rating					
Not Compatible	One or more of the following observed: Major flickering at various points, significant audible noise, no dimming range, does not turn off.				
Bad	One or more of the following observed: Some flickering observed at various points, audible noise may be present, dimming not smooth.				
Good	One or more of the following observed: Minor flickering at some point may exist. Dead travel may exist, which means there may be periods of time when the slider (or other form of control button) is moved without affecting the light level. These periods of dead travel are minor and most of the time not visible. Minor audible noise.				
Best	Most of the following observed: No flickering, minimal audible noise (typically less than 25 dBa), wide dimming range - can dim down to 20% or less of light output.				
High End (H.E.) Dead Travel	Determines how much, if any, dead travel exists at the top and bottom of the dimmer's range. Dead travel is when the slider can be moved without affecting the light level.				
Low End (L.E.) Dead Travel	Determines now mount, in any, usad daver exists at the top and bottom of the diffinites strange. Dead daver is when the shoet can be inoved without anecting the light level.				